


# CONTAORE DIGITALE ART. 00116



### Caratteristiche tecniche:

Gamma di indicazione 0-99999,9 ore  
Accuratezza: +/- 0.02%  
Memoria: > 25 anni senza alimentazione  
Auto test alla connessione dell'alimentazione  
Tensione di funzionamento: 10-80Vcc  
Consumo: < 10 mA

### Connessioni:

+) Positivo alimentazione  
-) Negativo alimentazione  
C) Abilitazione sotto chiave (positivo)  
R) Azzeramento strumento.

### Istruzioni:

Connettere lo strumento alla batteria utilizzando i terminali + e -.  
Il terminale C deve essere collegato tramite chiave al positivo della batteria: alla chiusura del contatto, lo strumento comincerà a contare, segnalando l'operazione con il lampeggio del simbolo della clessidra.  
Il terminale R deve essere utilizzato SOLO se si vuole azzerare il contaore: in questo caso bisogna connetterlo al negativo per almeno 2 secondi.

### Specifications:

Range: 0-99999,9 hours  
Accuracy: +/- 0.02%  
Memory: > 25 years without supply  
Self test at power on  
Operating range: 10-80Vdc  
Input: < 10 mA

### Wirings:

+) Positive supply  
-) Negative supply  
C) key switch enable (positive)  
R) Reset.

### Instructions:

Connect the instrument to the battery using + and - leads.  
The C lead must be connected to the positive through a key switch: when the contact closes, the instrument is enabled and a sandglass symbol will twinkle.  
The R lead must be used ONLY to reset the instrument: to do it, connect the lead to the negative for 2 seconds at least.

